

MPC 2500 V1.1 update procedure

***** BEFORE YOU BEGIN! *****

Please make sure to back up all contents of the internal hard drive **BEFORE** upgrading the OS. After upgrading, it is recommended that you format your internal hard drive.

How to copy OS bin file to CF with MPC2500 and Computer

Required Equipment: Compact Flash (CF), USB mass storage class supported computer (Windows XP/ME/2000 or Mac OSX, OS9.x)

1. Download the file MPC2500v110.ZIP from our website to your computer
2. Your browser should automatically unzip the file and you should have a file called MPC2500v110.bin on your computer
3. Insert Compact Flash into the MPC2500
4. Switch the MPC2500 on
5. Go to load mode, then press USB (F4)
6. Connect a USB cable between PC and the MPC2500 (display will change from 'Status=Not Connected' to 'Status=Connected')
7. PC will mount the CF card of the MPC2500 as a drive on your computer
8. Copy (drag) OS .bin file on to the CF
9. Once the file has been copied, safely dismount the MPC from your computer, and disconnect the USB cable

How to update MPC2500

1. From the LOAD screen, select the file MPC2500v110.bin
2. press [F6] (DO IT)
3. you will receive the following warning

OS update
This writes OS to Flash memory
This process requires system
restart. All memory contents
will be lost !!!

4. Press [F5] (DO IT)
5. The OS will begin loading.

***** IMPORTANT NOTE *****

DO NOT SWITCH OFF THE MPC2500 WHILE IT IS UPDATING THE OS!

6. When the OS has finished loading, you will be prompted to restart the MPC 2500. Go ahead and power cycle the unit.